To convert color codes for other brand pickups:

(adapted from Stewart-MacDonald's web site)

[A] __( )))))))))))__ [B]

[D] __( )))))))))))__ [C]

	A	B	C	D
Seymour Duncan	Black	White	Red	Green
DiMarzio	Red	White	Black	Green
Gibson	Black	Green	White	Red
PRS Neck	White	Red >>>	<<< Red	Black
PRS Bridge	Black	Red >>>	<<< Red	White
Lawrence	Black	Green	White	Red
Schaller	Green	White	Brown	Yellow
Jackson	Green	White	Red	Black
Anderson	Red	Green	White	Black

Series/Out of Phase [Standard HB Linkage]*

A -> Hot(+); B <--> C; D -> Ground

Series/In Phase [Non-Humbucking]

A -> Hot(+); B <--> D; C -> Ground

Parallel/Out-of-Phase ["Dual Sound" Linkage]**

A & C -> Hot(+); B & D -> Ground

Parallel/In Phase [Non-Humbucking]

A & D -> Hot(+); B & C -> Ground

* Normal humbucker wiring for full sound.

** Alt. humbucking wiring for a thinner sound.

Note: Some of the Hot and Ground colors are reversed.

Check the Stew-Mac site for updated information.